

USER MANUAL

Thank you for purchasing this product

For optimum performance and safety, please read these instructions carefully before connecting, operating or adjusting this product. Please keep this manual for future reference.

Surge protection device recommended

This product contains sensitive electrical components that may be damaged by electrical spikes, surges, electric shock, lightning strikes, etc. Use of surge protection systems is highly recommended in order to protect and extend the life of your equipment.

Table of Contents

1. Introduction.....	
2. Features.....	
3. Package Contents.....	
4. Specifications.....	
5. Operation Controls and Functions.....	
5.1. Front Panel.....	
5.2. Rear Panel.....	
5.3. Connecting to the Switcher.....	
5.4. Using the Switcher.....	
6. IR Remote.....	
7. Using the Built-In Web GUI Interface.....	
8. API Control Command.....	
9. Application Example.....	

1. Introduction

This high performance HDMI Matrix Switcher can switch any of these four HDMI 2.0 sources to four HDMI 2.0 displays. Each input and output supports up to 4K60 444 resolution and HDCP 2.2. The outputs can be individually scaled for 1080p. De-embedded audio as analog L/R and coaxial is available for both outputs. The ARC function can return display device audio to coaxial port output only. Advanced EDID management is supported. With its 18Gbps bandwidth and the additional features with latest HDMI standards. This switcher can be controlled from the front panel, RS-232, IR remote, or TCP/IP.

2. Features

- ☆ HDMI 2.0, HDCP 2.2 / HDCP 1.4 and DVI 1.0 compliant
- ☆ Four 18G HDMI 2.0 video inputs support up to 4K60 444 resolution
- ☆ Four 18G HDMI 2.0 video outputs support up to 4K60 444 resolution
- ☆ Four outputs can be individually scaled for 4K→1080p
- ☆ De-embedded audio to analog L/R and Coaxial ports output
- ☆ ARC audio return to the coaxial ports output only
- ☆ Built-in Web GUI for TCP/IP control
- ☆ Advanced EDID management supported
- ☆ Four methods of control: Front panel, RS-232, IR remote and TCP/IP
- ☆ Compact design for easy and flexible installation

3. Package Contents

- * 4x4 HDMI 2.0 18Gbps Matrix Switcher
- * 12V/2.5A Locking Power Adapter
- * IR Remote
- * Mounting Ears
- * 38K Hz IR Receiver Cable (1.5 meters)
- * 3-pin Phoenix Connector
- * User Manual